

**PURPOSE**

Used to plug off wellbore, used in conjunction with X/XN Lock assemblies.

**ASSEMBLY PARTS**

1. Prong Mandrel
2. End Cap
3. Housing
4. Housing Cap
5. Backup Ring - Female
6. Backup Ring - Double Male
7. Backup Ring - Double Female
8. V - Packing

**OPERATION**

Attach housing to appropriate lock mandrel and set in desired profile nipple using a X Running Tool. Dress prong with desired packing and lower into wellbore using a jar down Pulling Tool (an SB is recommended), jar into housing attached to bottom of lock mandrel at desired depth, jar down until pin in SB/JDC is sheared and prong is set.

To remove, latch prong with desired pulling tool (always ensure pressure is equalized) jar up until prong comes free. Once the prong has been retrieved, a GS or GR may be used to retrieve the lock and housing.

**PRECAUTIONS:**

Care should be taken to record wellbore pressure before plug is installed. This will aid in equalizing when retrieving operations commence.

\*Specify type of V - packing when ordering.

(Sizes on next page)

When ordering please specify part name and size. Call us Toll Free: 1-800-438-0061

Nominal Size		1.50"	1.625"	1.78"(R)	1.87"
Assembly Number		0902PX150A0	0902PX162A0	0902PR178(R)A0	0902PX200A0
Item	Part Name				
1	Prong Mandrel	0902PX15001	0902PX15001	0902PR178(R)01	0902PX20001
2	End Cap	0902PX15002	0902PX15002	0902PR178(R)02	0902PX20002
3	Housing	0902PX15003	0902PX16203	0902PR178(R)03	0902PX20003
4	Housing Cap	0902PX15004	0902PX15004	0902PR178(R)04	–
5	Backup Ring - Female	0902BUR06201	0902BUR06201	0902BUR08101	0902BUR09301
6	Backup Ring - Double Male	0902BUR06202	0902BUR06202	0902BUR08102	0902BUR09302
7	Backup Ring - Double Female	0902BUR06203	0902BUR06203	0902BUR08103	0902BUR09303
8	V - Packing*	0902VP16201	0902VP16201	0902VP18101M1	0902VP09301
Upper Thread Connection		1.125"-16 UN	1.125"-16 UN	1.375" - 14 UN	1.375" - 14 UN
Max O.D.		1.490"	1.615"	1.770"	1.865"
Fishneck size		1.00"	1.00"	1.187"	1.37"

Nominal Size		2.31"	2.75"	2.81"
Assembly Number		0902PX250A0	0902PX275A0	0902PX281A0
Item	Part Name			
1	Prong Mandrel	0902PX25001	0902PX30001	0902PX30001
2	End Cap	0902PX25002	0902PX30002	0902PX30002
3	Housing	0902PX25003	0902PX27503	0902PX28103
4	Housing Cap	–	–	–
5	Backup Ring - Female	0902BUR12501	0902BUR15001	0902BUR15001
6	Backup Ring - Double Male	0902BUR12502	0902BUR15002	0902BUR15002
7	Backup Ring - Double Female	0902BUR12503	0902BUR15003	0902BUR15003
8	V - Packing*	0902VP12501	0902VP15001	0902VP15001
Upper Thread Connection		1.75"-12 UN	2.25"-12 SLB	2.25"-12 SLB
Max O.D.		2.307"	2.745"	2.809"
Fishneck size		1.37"	1.37"	1.37"

When ordering please specify part name and size. Call us Toll Free: 1-800-438-0061